

M 23 SIGNAL



Inserts / Pinouts

Inserts 6-pole		Туре	Part Number	Part Number		
5 5 4 4 0 0 2	Insert pin mating view (Part E)	Pinout clockwise Insert with solder contacts	Pins 7.001.906.1037.003.906.101	Sockets 7.001.906.104 7.003.906.102		
		Insert with dip solder contacts Length 3,5 mm	7.001.906.107			
		Insert with dip solder contacts Length 10 mm	7.001.906.127	7.001.906.108		
	Insert socket mating view (Part P)	Insert with dip solder contacts Length 17 mm	7.001.906.137	7.001.906.118		
		The correct dimension of a connector with dip solder contacts depends on the particular type of housing.				
4.75		Coding possibilities N, S, H, X and Y (see page 81)				
4,75						
		▶82/83				

Inserts 7-pole		Туре	Part Number	Part Number
	Insert pin mating view (Part E)	Insert without contacts	Pins7.001.907.1037.003.907.101	
	Insert socket mating view (Part P)	Insert with dip solder contacts Length 17 mm	7.001.907.1077.001.907.127	7.001.907.118
4,75		Coding possibilities N, S, H, X and Y (see p	age 81)	

▶82/83

